

BELLA

15W ALL IN ONE WIRELESS CHARGING GADGET



I. Function Buttons



- 1. Phone Charging Area 2. Watch charging Area 3. PM
- 4. Alarm Clock Indicator 5. Earbud Charging Area 6. M Button
- 7. Snooze Button 8. + Button 9. - Button 10. Earbud Charging Indicator
- 11. Phone Charging Indicator

II. Operation manual

- 1. Power Connection
- 1.1 Plug the USB-A/USB-C end of cable into the power adapter while plug Type-C end into the product, then the product can enter the normal working state.

2. Wireless Charging

- 2.1** This product can charge mobile phones, earbuds and watches at the same time.
- 2.2** The charging part of the watch is designed with a USB plug-in structure, making it easy to carry; Special magnetic suction automatic flipping structure, the watch charging module is compatible with both Apple smart watches and Samsung smart watches.

2.3 The clock part is designed as a USB plug-in structure, which can save space when not in use; USB can also provide 5V wired charging for your device.

2.4 Wireless charging status indicator (mobile phone and earbud have charging indicator, while watch without charging indicator)

Indicator Display: Power connected successfully –turn off after flashing twice

Standby – light off

Charging – light stays on

Fully charged – light off (Some iphone models do not support this function)

FOD – light flashes

3. Alarm Clock Functions

3.1 Buttons

Four Buttons: M Button Snooze Button +Button -Button

3.2 Time System Setting

Double click M button to setup 12-hour time system and 24-hour time system. In the 12-hour time system, PM will be displayed after 12:00.

3.3 Time Setting

3.3.1 Click M button once to enter Hour setting, adjust the value with +/- button; Press and hold the +/- button to adjust continuously.

3.3.2 After finishing the Hour setting, Click M button once to enter Minute setting, adjust the value with +/- button; press and hold the +/- button to adjust continuously.

3.3.3 Click M Button once to exit after the minute setting complete, or automatically exit after timeout.

3.4 Alarm Clock Setting

3.4.1 Press and hold the "+/-" button to turn on the alarm clock, press and hold the "+/-" button to turn off the alarm clock, after turning on the alarm clock, the indicator light will be on.

3.4.2 While Alarm clock activated, press M button 3 seconds to enter alarm Hour setting, adjust the value with +/- button; Press and hold the +/- button to adjust continuously.

3.4.3 After finishing the Hour setting, click M button once to enter alarm Minute setting, adjust the value with +/- button; press and hold the +/- button to adjust continuously.

3.4.4 Click M button to end the setting after the minute setting complete, or automatically exit after timeout.

3.4.5 After alarm clock rings, it automatically turn off the alarm clock of the current day after 3 minutes while no any operation or Long Press Snooze button to turn off the alarm clock of the current day after the alarm ring, the alarm clock setting for next day is still valid. Long press the "+/-" button to turn off the alarm clock permanently.

3.4.6 Touch any button to enter snooze mode when alarm bell rings. Bell rings for unlimited times after 5 minutes, ring for 3 minutes, the indicator flashes during the snooze mode. Long press the SNOOZE button in the Sleepy Mode to turn off the alarm clock of the current day and the alarm clock of the next day is still valid; Long press the "+/-" button to turn off the alarm clock permanently.

Short press the snooze button in the normal display state to check the set alarm clock for 5 seconds. If the alarm clock is not set, the button will be invalid.

3.5 Display Brightness Setting

3.5.1 The clock brightness can be adjusted manually in 5 levels (Max, Second, Medium, Low, Off) adjust the light brightness of the digital display with +/- button, after connecting to power, the light brightness of the digital display is the brightest by default. Click the "-" button once to reduce the brightness by one level, click the "+" button once to increase the brightness by one level; the last click to turn off the display light.

click to turn off the night light.

3.6 Power saving function

3.6.1 After the power is disconnected, the internal button battery can be used to memorize the clock setting, and the clock does not need to be reset after the power connected again.

3.6.2 All functions are out while unplug the external power supply, functions restored when power is connected.

4. Cautions

In order to ensure alarm clock, wireless charging, clock and light night work at the same time, power shall be connected a QC3.0 and above or PD adapter. When powered by 5V voltage, the wireless charger only supports 5W load or clock function.

4.1 Do not squeeze or collide.

4.2 Do not disassemble or put into the fire, water, to avoid short-circuit leakage.

4.3 Do not use wireless chargers in severe high temperature, humidity or corrosive environments to avoid leakage of damaged circuits.

4.4 Do not place it too close to magnetic cards (ID cards, bank cards, etc.) with magnetic strips or chips to avoid magnetic card failure.

4.5 Keep more than 20cm between the implanted medical device (pacemaker, implantable cochlea, etc.) and the wireless charger to avoid potential disruption to medical devices.

4.6 Keep children from the product in case they play the wireless charger as a toy to avoid accidents.

4.7 Keep the wireless charger and receiver device away from water and other liquids.

4.8 To clean the charger, make sure the power supply is disconnected.

4.9 Usage temperature: 0-45°C

4.10 Usage humidity: 20-85% (40RH)

Warning: This product contains button battery, which can cause serious or fatal injury within 2 hours if swallowed. Batteries must be kept away from children. If you think the battery may have been swallowed or placed anywhere in your body, please seek medical assistance immediately.

* The pictures involved in this manual are all illustration. Final product is subject to the actual object.

* Inside package including: Clock wireless charger, USB charging cable, User manual.

* Power adapter is not included. Please purchase otherwise or use original adapter with the phone.

III. Specification

Input	: DC 5V/3A; 9V/3A; 12V/2A
Output	: Phone: 15W (compatible with 10W, 7.5W, 5W)
Earbud	: 5W (MAX)
Watch	: 2.5W (Compatible with both Samsung and Apple smart Watches)
Charging efficiency	: 73%
Transmission distance	: ≤2-5mm
Work frequency	: 110-205KHz
Product size	: 143*33*178mm